

HISTORY BASED MEASURED POWER CONTROL RESPONSE

Related Applications

[0001] This application claims the benefit of prior filed provisional application 60/398,264, filed on July 23, 2002.

I. Field of the Invention

[0002] The present invention relates to the field of wireless communications. More particularly the present invention relates to method and apparatus for responding to power control instructions received on a reverse link of a channel, in the context of queuing and batch processing received transmission frames.

II. Background of the Invention

[0003] Advances in satellite communication and related technology have led to rapid deployment of mobile satellite services (MSS) in recent years. While economic factors have slowed the growth of these systems, tens of thousands of user terminals are currently in use, providing valuable services in areas that otherwise would not have communications services.

[0004] Delivery of mobile satellite services, in addition to the user terminals, typically includes the provision of space vehicles, i.e. satellites, and a number of gateways, also referred to as base stations. The satellites serve as "relays" between the gateways and the user terminals.

[0005] Power controls are often employed to manage the exchange of signals between a user terminal and a gateway via one or more satellites. In particular, power control instructions, in the form of e.g. power control bits, are often included in or with the transmission frames received on a reverse link of a channel (also referred to as a return link of the channel).

[0006] In the context of MSS, a channel corresponds to an assigned frequency. In the context of multi-access, such as in the case of Time Division Multiple Access (TDMA), a channel is divided into multiple time slots, with one or more time slots assigned to each user terminal. The aggregate of these time slots, plus some overhead data bits, corresponds to a transmission frame. Analogously, in the case of Code Division

Multiple Access, a channel is shared among simultaneous users by encoding the transmissions for each user with an orthogonal or nearly orthogonal spreading code.

[0007] Increasing the number of users, and the usage by the users, results in increased data traffic, which in turn translates into an increased amount of transmissions from the user terminals and processing to be performed by the gateways. To facilitate handling of the increased amount of processing, some gateways may desire to queue the transmission frames received on the reverse link of a channel and process them in batches.

[0008] Power control is important in CDMA systems for optimal capacity, so each transmission frame for user traffic (e.g., voice or data) typically carries a power control instruction (typically a single bit, indicating power up or down one increment) for the transmitter at the other end of the communication link. If the power control instructions are responded to in the same manner in the queued/batched processing context as they are responded to in the real time non-queued/un-batched processing context, acting upon excessive consecutive identical power control commands might result due to the delay inserted in the power control loop by the queuing. In turn, the excessive consecutive issuance of identical power control commands may lead to the loss of the channel or communication link.

[0009] Thus, an improved approach to responding to power control instructions, when transmission frames are queued or processed in batches, is desired.

SUMMARY OF THE INVENTION

[0010] Briefly, the present invention provides a method and apparatus to slow the response or response rate to power control instructions that are determined or generated by a receiver on a communications link for an opposite or corresponding transmitter, and included with each frame received on a link of a channel. If the receiver determines that the opposite or correspondingly received transmission is too weak, it will include a power-up command recommendation with the received frame and vice versa.

[0011] Under operating conditions, a first plurality of frames received over a link are queued for later processing in batches. To slow the response to power control instructions included with the received frames, the instructions or commands are examined, and a running history of predetermined length is kept. A second plurality of frames to be transmitted on the opposite direction link of the channel are also queued for later handling in batches. Power control instructions are generated for inclusion

with the queued frames to be transmitted, based at least in part on the history being kept or maintained, to effectuate the desired slowing of response to the incoming power control instructions.

[0012] In accordance with one aspect of the present invention, the power control instructions and responses are in a form of power control bits, and the predetermined length of the history is on the order of 2 bits, for a typical communication system or link. The number m of “zero” value power control bits and the number n of “one” value power control bits generated for inclusion with the frames to be transmitted, are dependent on the bit pattern of the 2-bit history, and whether or not the second plurality of frames contains an even or odd number of frames, and the two values may be equal or differ by say 1.

[0013] The method or apparatus keeping and generating operations may be performed in a gateway of a wireless communication system, or in an emulated gateway and a gateway simulator of a wireless communication test system.

[0014] In further aspects, the wireless communication system gateway uses a transceiver to receive a first plurality of frames on a link of a channel, and queues the first frames for processing in batch form, each of the frames including a power control instruction, and outputs the power control instruction included with each of the first plurality of frames. A processing subsystem coupled to the transceiver processes or examines the information in the queued first frames to receive the power control instructions, and to generate a second plurality of frames for a return direction link over the channel, such frames also being queued before being handled by or processed in the transceiver. The processing subsystem: keeps a running history of the examined power control instructions included with the first frames, up to a predetermined length of time, and generates power control commands for the second frames based at least in part on this retained or maintain running history being, in a manner that effectuates slowing of a response or response rate to the power control instructions.

[0015] In further aspects of the gateway, the processing subsystem is designed to generate m “zero” value power control bits and n “one” value power control bits for each batch formed with the second plurality of frames, the number being dependent upon whether or not there are an even or odd number of frames, and information bit values of the control commands..

[0016] In further embodiments, wireless communication apparatus is provided having a gateway emulator configured to emulate receipt of a first plurality or set of frames in

one direction on a link of a channel, and grouping or queuing these first frames for processing in batch form, the frames including or accompanied by power control instructions. The gateway emulator provides power control instructions with each of the first set of frames. A gateway simulator coupled to the gateway emulator processes the queued first frames in batch form and receives or detects the value of power control instructions processed by the gateway emulator, and generates a second plurality of frames for a return direction link of the channel, which are also queued before being handled by the gateway emulator in batch form. The gateway simulator keeps a running history, up to a predetermined length, of the power control instructions included with the first set of frames, and generates corresponding power control commands for the second set of frames based at least in part on the maintained running history, in a manner that effectuates a slowing of responses to the power control instructions. The gateway simulator is designed to generate m "zero" value power control bits and n "one" value power control bits, as desired, for each batch formed with a subset of the second frames.

[0017] In further embodiments, apparatus for realizing the advantages and features of the invention is provided having means for keeping a running history, up to a predetermined length, of power control instructions included with a first plurality of frames received in one direction on a link of a communications channel, which frames grouped before their processing, and means for generating power control commands for a second plurality of frames to be transmitted in an opposing direction over the link on the channel, based at least in part on the maintained running history, in a manner that effectuates a slowing response to the incoming power control instructions, with the second frames also being grouped for subsequent processing in batch form for transmission.

[0018] The operations of the invention may be realized using a machine readable medium having stored thereon machine executable instructions that when executed implement a method comprising maintaining a running history, up to a predetermined time or length, of power control instructions included with a first plurality of frames received on a link of a channel, the first frames being grouped before their processing; and generating power control commands for a second plurality of frames to be transmitted on the link for the channel in a reverse direction, based at least in part on the running history being detected and maintained, in a manner that effectuates a slowing of

response or response rate to received power control instructions, with the second frames also being grouped for subsequent processing in batch form for transmission.

BRIEF DESCRIPTION OF THE DRAWINGS

- [0019] Examples of the present invention are illustrated by way of example in the accompanying drawings. The drawings do not, however, limit the scope of the present invention. Similar references in the drawings indicate similar elements.
- [0020] FIG. 1 illustrates a method of the present invention, in accordance with one embodiment;
- [0021] FIG. 2 illustrates the history based power control generation of FIG. 1 in further detail, in accordance with one embodiment;
- [0022] FIG. 3 illustrates an example gateway within which the present invention may be practiced, in one embodiment;
- [0023] FIG. 4 illustrates a satellite based wireless communication system, within which the example gateway of FIG. 3 may be used, in one embodiment;
- [0024] FIG. 5 illustrates an example gateway emulator and an example gateway simulator within which the present invention may be practiced, in one embodiment;
- [0025] FIG. 6 illustrates a wireless communication test system, within which the example gateway emulator and simulator of FIG. 5 may be used, in one embodiment;
- [0026] FIG. 7 illustrates one embodiment of a hardware system to implement various embodiments; and
- [0027] FIG. 8 illustrates one embodiment of a machine-readable medium to store executable instructions to implement various embodiments.

DETAILED DESCRIPTION OF EMBODIMENTS

- [0028] Various embodiments of the methods and apparatus to slow responding to power control instructions to reduce the likelihood of issuing an excessive number of consecutive power control instructions that might lead to the loss of a channel or communication link in wireless communication for a wireless communication system or device, will now be described.
- [0029] In the description to follow, various aspects of these embodiments will be described. However, it will be apparent to those skilled in the art that the present invention may be practiced with only some, or with all aspects of these embodiments described. For purposes of explanation, specific numbers, materials and configurations

are set forth in order to provide a thorough understanding of the present invention. However, it will also be apparent to one skilled in the art that the present invention may be practiced without the specific details. In other instances, well-known features are omitted or simplified in order not to obscure the present invention.

[0030] Reference herein to “one embodiment”, “an embodiment”, or similar formulations, means that a particular feature, structure, operation, or characteristic described in connection with the embodiment, is included in at least one embodiment of the present invention. Thus, the appearances of such phrases or formulations herein are not necessarily all referring to the same embodiment. Furthermore, various particular features, structures, operations, or characteristics may be combined in any suitable manner in one or more embodiments.

A Generic Embodiment

[0031] Referring now to FIG. 1, wherein a block diagram illustrating a generic embodiment of the invention is shown. This generic embodiment includes, in particular, batching logic **104** and power control command generator/stuffer **118**, both incorporated within the teachings of the invention. The embodiment also includes a storage location, element, or device **110**. Additionally, the embodiment also includes batch processing logic **108**, and frame generator **114**. The elements are operationally coupled to each other as shown.

[0032] Batching logic **104** is employed to queue or group together or batch received transmission frames **102** on a link of a channel, e.g. the reverse or return link (RL) where signals are transferred from a transmitter in a user terminal to a receiver in a gateway, into frame batches **106**, for subsequent processing in batch, e.g., by batch processing logic **108**. Additionally, it is employed to output the power control instructions **R** included with the received transmission frames **102**, thus enabling a running history of the included power control instructions, up to a predetermined length or period of time, to be kept or maintained.

[0033] For an embodiment, storage **110** is employed to store, contain, or hold the running history, up to a predetermined length. As will be described in more detail below, the running history is employed in the generation of the power control responses or commands used to slow down the response actions or responding to the power control instructions, thereby reducing the likelihood of issuing excessive consecutive power control commands, which might lead to the loss of the channel.

- [0034] Batch processing logic **108**, as its name suggests, is employed to process the frame batches **106**. The exact nature of the processing performed is not relevant to practice of the present invention, and is understood by those skilled in the art for the system of interest.
- [0035] Frame generator **114** is employed to organize the transmit traffic/signals to be transmitted on a link of a channel, e.g. the forward link (FL) where signals are transferred from a transmitter in a gateway to a receiver in a user terminal, into frames **116**. The manner in which transmit traffic/signals is framed also is not relevant to the practice of the present invention and is understood by those skilled in the art for the specific communication system being employed.
- [0036] Power control command generator/stuffer **118** is employed to generate and insert power control commands **P** into frames **116** to be transmitted on the forward link of the channel. For this embodiment, it also queues frames **116** into frame batches **120** for subsequent handling by a typical transceiver subsystem (not shown) in batches or groups.
- [0037] Thus, operationally, as transmission frames **102** are received on the reverse or return link of a channel, transmission frames **102** are queued or batched together by batching logic **104** into RL frame batches **106** for subsequent processing in batch, e.g., by batch processing logic **108**. Concurrently, a running history of the included power control instructions, up to a predetermined length, or time period, is kept in storage **110**, for subsequent use in slowing response to the power control instructions.
- [0038] As transmit traffic and signals **112** are being organized into transmission frames **116** by frame generator **114**, for transmission on the forward link of the channel, the generated frames **116** are also provided to power control response generator/stuffer **118** to have power control responses generated and inserted to transfer with the transmission frames **116**.
- [0039] In accordance with embodiments, generator/stuffer **118** generates the power control responses based at least in part on the running history being maintained in storage **110**. More specifically, as described earlier, it generates the power control commands based at least in part on the running history kept, in a manner that slows the response to the power control instructions, thereby reducing the likelihood of over issuing consecutive power control commands, which may lead to the loss of a channel. For example, issuing excessive power decrease commands, which cause the channel to drop below a useful power level to either maintain a link or connection, or to increase

errors in reception. Likewise, excessive issuance of power increase commands could cause a user terminal to use too much power and cause interference with other user terminals or signals, as well as unnecessarily consume valuable power supply resources.

[0040] For the embodiment, at least selected ones of transmission frames **102** include power control instructions in the form of power control bits. These power control bits are output by batching logic **104** as it queues or batches the received frames **102** into frame batches **106**. The power control bits are examined and their values or control information being provided is successively stored in storage **110**, in the form of a queue. An exemplary queue has a queue length on the order of 2 bits. However, other queue lengths may be employed as desired, depending among other things on the amount of command information to be stored.

[0041] Generator/stuffer **118** generates the power control commands based at least in part on the running history in the queue, here 2-bit, being kept. More specifically, for one embodiment, it generates the power control commands based at least in part on the running 2-bit history kept, in a manner that slows the response to the power control instructions to approximately the rate of batch processing, to be described in more detail with reference to FIG. 2.

[0042] Besides accruing a copy or version of the power control instructions for history keeping purposes, batching logic **104**, batch processing **108** and frame generator **114**, all represent a wide range of these elements known in the art. Accordingly, they will not be further described. Implementing outputting of the power control instructions while batching the received frames is well within the ability of those skilled in the art, thus it too need not be further described in detail here.

Power Control Command Generation

[0043] FIG. 2 illustrates the operational flow of the relevant aspects of power control command generator/stuffer **118** of FIG. 1, in accordance with one embodiment. The embodiment assumes the power control instructions *R* and commands *P* are in the form of power control bits, and a running 2-bit history of the power control bits included with the received frames are kept.

[0044] As illustrated, in the relevant part, generator/stuffer **118** determines whether or not the 2-bit history has either the bit pattern of “01” or “10”, in a step or processing stage **202**. If it is determined that the 2-bit history has either of the two bit patterns, generator/stuffer **118** generates approximately equal numbers of “zero” value and “one”

value power control command bits, i.e. m “zero” value power control response bits, and n “one” value power control response bits, with m and n being different at most by 1, m and n are both integers, stage **204**.

[0045] If there are an even number of frames, the number of “zero” value and “one” value power control command bits generated, i.e. m and n , are equal. If there are an odd number of frames, the batches will alternate having the number of “zero” value power control command bits generated (m) greater than “one” value power control response bits generated (n) by “1”.

[0046] In one embodiment, the batches occupying the odd ordinal positions, in terms of batch generation, will have m greater than n by 1, and the batches occupying the even ordinal positions, in terms of batch generation, will have n greater than m by 1.

[0047] In another embodiment, the arrangement is reversed, i.e. the batches occupying the odd ordinal positions, in terms of batch generation, will have n greater than m by 1, and the batches occupying the even ordinal positions, in terms of batch generation, will have m greater than n by 1.

[0048] If at step or stage **202**, it is determined that the 2-bit history does not have either the “01” or “10” bit pattern, generator/stuffer **118** further determines whether or not the 2-bit history has the bit pattern of “11”. If it is determined that the 2-bit history has the bit pattern of “11”, generator/stuffer **118** alternates in generating “one” value power control command bits, and “zero” value power control command bits, with one or two extra “one” value power control command bits, depending on whether there are odd or even numbers of frames in a batch, step **208**.

[0049] When there are an odd number of frames in a batch, the batch is formed naturally with an extra “one” value power control command bit. When there are an even number of frames in a batch, generator/stuffer **118** generates the last bit as a “one” value power control bit also, thereby making the last two power control command bits, “one” value bits. Accordingly, the number of “one” value power control command bits generated will exceed the number of “zero” value power control bits by 2.

[0050] If at step or processing stage **204**, it is determined that the 2-bit history does not have the “11” bit pattern, nor the other patterns discussed above, the 2-bit history by default has the “00” bit pattern. Generator/stuffer **118** alternates in generating “zero” value power control command bits, and “one” value power control response bits, with one or two extra “zero” value power control command bits, depending on whether or not there are an odd or even number of frames in a batch, step **210**.

[0051] When there are an odd number of frames in a batch, the batch is formed naturally with an extra “zero” value power control command bit. When there are an even number of frames in a batch, generator/stuffer **118** generates the last bit as a “zero” value power control bit also, thereby making the last two power control command bits, “zero” value bits. Accordingly, the number of “zero” value power control command bits generated will exceed the number of “one” value power control bits generate by 2.

A Gateway Embodiment

[0052] Referring now to FIG. 3, wherein a block diagram illustrating a gateway embodiment of the present invention is shown. The terms gateway, hub, and base station, are sometimes used interchangeably in the art, with gateways being perceived as specialized base stations that direct communications through satellites, while base stations use terrestrial antennas to direct communications within a surrounding geographical region. The expression ground station is sometimes used interchangeably in this field with gateway.

[0053] Similar to the generic embodiment illustrated by FIG. 1, gateway **300** includes the earlier described batching logic **104** and power control command generator/stuffer **118**, both incorporated within the teachings of the present invention. This embodiment also includes storage element, location, or device **110**. Additionally, the embodiment also includes batch processing logic **108** and frame generator **114**.

[0054] For the gateway embodiment, batching logic **104** is a component of a transceiver subsystem **302**, whereas batch processing **108**, storage **110**, frame generator **114** and power control command generator/stuffer **118** are components of a frame processing subsystem **304**.

[0055] The elements are operationally coupled to each other as shown. Further, the elements are used and cooperate with one another as earlier described.

[0056] In particular, in one embodiment where the power control instructions are in the form of power control bits, storage **110** holds a 2-bit running history in a queue form as earlier described, and generator/stuffer **118** generates slowed response to the power control bits in a manner as earlier described in reference to FIG. 2.

[0057] Beside the teachings of the present invention incorporated in transceiver subsystem **302** and frame processing **304**, the elements are otherwise known in the art, and accordingly will not be further described herein.

Application of the Gateway Embodiment

[0058] FIG. 4 illustrates a MSS within which gateway 300 endowed with the slowed or slower power control response of the present invention, may be employed. As illustrated, the MSS includes user terminals 430 and 440 and gateway 300, bridged by communication satellite 420. First user terminal or terminal device 430 receives transmissions from communications satellite 420 via a forward link of a first channel of a first beam 435, and transmits to communications satellite 420 on the reverse link of the first channel. Second terminal device 440 receives transmissions from communication satellite 420 via a forward link of a second channel of a second beam 445, and transmits to the communication satellite 420 on the reverse link of the second channel.

[0059] It is contemplated for this example that satellite 420 provides multiple beams within at least one 'spot' that are directed to cover separate generally non-overlapping geographic regions. Generally, multiple beams at different frequencies, also referred to as CDMA channels (when using CDMA), 'sub-beams' or FDM signals, frequency slots, or channels, can be directed to overlap the same region. However, it is readily understood that the beam coverage or service areas for different satellites, or antenna patterns for terrestrial cell-sites, may overlap completely or partially in a given region depending on the communication system design and the type of service being offered.

[0060] To establish the forward or reverse links, the channels may be sub-divided into time slots, as used for TDMA type communications systems or signals, or into code channels, as used by CDMA type communication systems or signals, with each terminal communicating over an assigned code channel. As is well known, these and other combinations can be used to establish the links within channels being discussed herein.

[0061] The terms reverse link and forward link were discussed above. The terms reverse link and return link are sometimes used interchangeably in this field, and refer to communication pathways by which signals propagate from a terminal device to a satellite, and from the satellite to a ground station. In terrestrial communication systems, they propagate from a terminal to a base station directly. Forward link refers to communication pathways by which signals propagate from a ground station to a satellite, and from the satellite to a terminal device. In terrestrial communication systems, they propagate from a base station to a terminal directly. In addition, the terms "reverse direction" is used to imply transfer or transmission of signals over a

communication link in a direction (RL or FL) in an opposite direction (FL or RL) from those received. This is well understood by those skilled in the art.

[0062] User terminals or terminal devices **430** and **440** each have or comprise a wireless communication device such as, but not limited to, a cellular telephone, a data transceiver or a transfer device (e.g., computers, personal data assistants, facsimile). Typically, such units are either hand-held or vehicle mounted as desired. While these user terminals are discussed as being mobile, it is also understood that the teachings of the invention are applicable to fixed units or other types of terminals where remote wireless service is desired. This latter type of service is particularly suited to using satellite repeaters to establish communication links in many remote areas of the world. User terminals, terminals devices, or user terminals, are also sometimes referred to as wireless devices, access terminals, subscriber units, mobile units, mobile stations, or simply "users," "mobiles," or "subscribers" in some communication systems, depending on preference. These terms are well understood in this field.

[0063] Gateway **300** transmits forward channel data to terminal devices **430**, **440** through communications satellite **420**, and receives reverse channel data from terminal devices **430**, **440** also through communications satellite **420**.

[0064] The reverse channel data may include power control instructions, in particular, power control instructions in the form of power control bits. Gateway **300** endowed with the teachings of the present invention, is able to batch process the received reverse channel data, and at the same time, by slowing the response to the power control instructions, reduces the likelihood of issuing excessive consecutive power control commands, and losing the channels.

[0065] Except for the teachings of the present invention included in gateway **300**, the rest of the elements are known in the art, and accordingly will not be further described.

A Gateway Emulator and Simulator Embodiment

[0066] As those skilled in the art would appreciate, development of a MSS requires extensive testing. Field or live testing is often expensive. Thus, a substantial amount of the testing is conducted in the development laboratory, under an emulated and/or simulated environment.

[0067] FIG. 5 illustrates a gateway emulator and simulator embodiment of the present invention. Also similar to the generic embodiment illustrated by FIG. 1, the emulator and simulator pair **502** and **504** includes the earlier described batching logic **104** and

power control response generator/stuffer **118**, both incorporated within the teachings of the present invention. The embodiment also includes storage **110**. Additionally, the embodiment also includes batch processing logic **108** and frame generator **114**.

[0068] For the embodiment, batching logic **104** is a component of emulator **502**, whereas batch processing **108**, storage **110**, frame generator **114** and power control response generator/stuffer **118** are components of simulator **304**.

[0069] The elements are operationally coupled to each other as shown. Further, the elements are used and cooperate with one another as earlier described.

[0070] In particular, in one embodiment where the power control instructions are in the form of power control bits, storage **110** holds a 2-bit running history in a queue form as earlier described, and generator/stuffer **118** generates slowed response to the power control bits as earlier described referencing FIG. 2.

[0071] Besides the teachings of the present invention incorporated in gateway emulator **502** and simulator **504**, the elements may include other components, such as networking and other interfaces for interfacing with each other and with other elements, such as user terminals and so forth. The exact composition of emulator **502** and simulator **504** is not essential to the practice of the present invention, and accordingly will not be further described.

Application of the Gateway Emulator and Simulator Embodiment

[0072] FIG. 6 illustrates a MSS testing environment within which emulator and simulator **502-504** endowed with the slowed power control response of the present invention may be employed. For the embodiment, in addition to the emulator and simulator pair **502-504**, MSS testing environment **600** includes user terminal **606** and a mobile communication subsystem (MCS) **608**.

[0073] Emulator **502** includes in particular, a number of networking interfaces, such as Ethernet interfaces, a radio frequency (RF) interface, and a timing and frequency unit (TFU) (all not shown), and simulator **504** includes a networking interface, and a diagnostic monitor (also not shown).

[0074] Emulator **502** and simulator **504** are coupled to each other via the networking connection, and exchange commands and data with each other over the networking connection, to allow simulator **504** to drive emulator **502** for the purpose of testing the MSS.

- [0075] User terminal **606** communicates with MCS **608** over one or more radio frequencies (RF), and communicates with gateway simulator **504** over a UT-DMI (diagnostic monitor interface), to allow gateway simulator **504** to drive it for the purpose of testing.
- [0076] MCS **608** in turn communicates with emulator **502** over the networking interface, for control commands, over RF, for user data, and over the TFU connection for timing and frequency information.
- [0077] Again, except for the teachings of the present invention endowed in gateway emulator and simulator **502-504**, the exact constitution and operation of the remaining elements are non-essential to the practice of the present invention to slow the speed or response rate to power control instructions, in particular, in the context of batch processing transmission frames.

Implementation

- [0078] Various aspects of the present invention may be implemented as circuit-based solutions, including possible implementation on a single integrated circuit. As would be apparent to one skilled in the art, various functions of circuit elements may also be implemented as processing operations in a software program. Such software may be employed in, for example, a digital signal processor, micro-controller, or general-purpose computer.
- [0079] Various embodiments of the present invention use computational resources to carry out the above-described functionality. Fig. 7 illustrates one embodiment of a hardware system intended to represent a broad category of computer systems such as personal computers, workstations, and/or embedded systems. In the illustrated embodiment, the hardware system includes processor **710** coupled to high speed bus **705**, which is coupled to input/output (I/O) bus **715** through bus bridge **730**. Temporary memory **720** is coupled to bus **705**. Permanent memory **740** is coupled to bus **715**. I/O device(s) **750** is also coupled to bus **715**. I/O device(s) **750** may include a display device, a keyboard, one or more external network interfaces, etc.
- [0080] Certain embodiments may include additional components, may not require all of the above components, or may combine one or more components. For instance, temporary memory **720** may be on-chip with processor **710**. Alternatively, permanent memory **740** may be eliminated and temporary memory **720** may be replaced with an electrically erasable programmable read only memory (EEPROM), wherein software

routines are executed in place from the EEPROM. Some implementations may employ a single bus, to which all of the components are coupled, or one or more additional buses and bus bridges to which various additional components can be coupled. Those skilled in the art will be familiar with a variety of alternative internal networks including, for instance, an internal network based on a high speed system bus with a memory controller hub and an I/O controller hub. Additional components may include additional processors, a CD ROM drive, additional memories, and other peripheral components known in the art.

[0081] In one embodiment, as described above, is implemented using one or more hardware systems such as the hardware system of FIG. 7. Where more than one computer is used, the systems can be coupled to communicate over an external network, such as a local area network (LAN), an internet protocol (IP) network, etc. In one embodiment, the present invention is implemented as software routines executed by one or more execution units within the computer(s). For a given computer, the software routines can be stored on a storage device, such as permanent memory **740**.

[0082] Alternatively, as shown in FIG. 8, the software routines can be machine executable instructions **810** stored using any machine readable storage medium **820**, such as a diskette, CD-ROM, magnetic tape, digital video or versatile disk (DVD), laser disk, ROM, flash memory, etc. The series of instructions need not be stored locally, and could be received from a remote storage device, such as a server on a network, a CD ROM device, a floppy disk, etc., through, for instance, I/O device(s) **750** of FIG. 7.

[0083] From whatever source, the instructions may be copied from the storage device into temporary memory **720**, and then accessed and executed by processor **710**. In one implementation, these software routines are written in the C programming language. It is to be appreciated, however, that these routines may be implemented in any of a wide variety of programming languages.

[0084] In alternative embodiments, the present invention is implemented in discrete hardware or firmware. For example, one or more application specific integrated circuits (ASICs) could be programmed with one or more of the above described functions of the present invention. In another example, one or more functions of the present invention could be implemented in one or more ASICs on additional circuit boards, and the circuit boards could be inserted into the computer(s) described above. In another example, field programmable gate arrays (FPGAs) or static programmable gate arrays (SPGA) could be used to implement one or more functions of the present invention. In yet

another example, a combination of hardware and software could be used to implement one or more functions of the present invention.

Conclusion

[0085] Accordingly, a history based method and apparatus which decreases the speed at which responses to power control instructions are implemented in MSS applications have been described.

[0086] An advantage of the present invention is to reduce the likelihood of over issuing consecutive power control commands, which might lead to the loss of a channel or communication link, in particular, when transmission frames are grouped together, queued, or batched for processing.

[0087] Although the invention is described primarily in terms of wireless, satellite-based communications, the present invention may be applicable to other types of communications channel(s), including digital, electrical or optical, wireless or wire/fiber, etc. where signal delay is an element of the communication links that one desires to compensate for.

[0088] It is to be understood that the present invention is not limited to the embodiments described above, but encompasses any and all embodiments within the scope of the subjoined claims.